

## 5 Electrical characteristics

$V_I = 10 \text{ V}$ ,  $I_O = 1 \text{ A}$ ,  $T_J = 0 \text{ to } 125 \text{ }^\circ\text{C}$  (L7805AC),  $T_J = -40 \text{ to } 125 \text{ }^\circ\text{C}$  (L7805AB), unless otherwise specified.

Table 3. Electrical characteristics of L7805A

Symbol	Parameter	Test conditions	Min.	Typ.	Max.	Unit
$V_O$	Output voltage	$T_J = 25 \text{ }^\circ\text{C}$	4.9	5	5.1	V
$V_O$	Output voltage	$I_O = 5 \text{ mA to } 1 \text{ A}$ , $V_I = 7.5 \text{ to } 18 \text{ V}$	4.8	5	5.2	V
$V_O$	Output voltage	$I_O = 1 \text{ A}$ , $V_I = 18 \text{ to } 20 \text{ V}$ , $T_J = 25 \text{ }^\circ\text{C}$	4.8	5	5.2	V
$\Delta V_O^{(1)}$	Line regulation	$V_I = 7.5 \text{ to } 25 \text{ V}$ , $I_O = 500 \text{ mA}$ , $T_J = 25 \text{ }^\circ\text{C}$		7	50	mV
		$V_I = 8 \text{ to } 12 \text{ V}$		10	50	mV
		$V_I = 8 \text{ to } 12 \text{ V}$ , $T_J = 25 \text{ }^\circ\text{C}$		2	25	mV
		$V_I = 7.3 \text{ to } 20 \text{ V}$ , $T_J = 25 \text{ }^\circ\text{C}$		7	50	mV
$\Delta V_O^{(1)}$	Load regulation	$I_O = 5 \text{ mA to } 1 \text{ A}$		25	100	mV
		$I_O = 5 \text{ mA to } 1.5 \text{ A}$ , $T_J = 25 \text{ }^\circ\text{C}$		30	100	
		$I_O = 250 \text{ to } 750 \text{ mA}$		8	50	
$I_q$	Quiescent current	$T_J = 25 \text{ }^\circ\text{C}$		4.3	6	mA
					6	mA
$\Delta I_q$	Quiescent current change	$V_I = 8 \text{ to } 23 \text{ V}$ , $I_O = 500 \text{ mA}$			0.8	mA
		$V_I = 7.5 \text{ to } 20 \text{ V}$ , $T_J = 25 \text{ }^\circ\text{C}$			0.8	mA
		$I_O = 5 \text{ mA to } 1 \text{ A}$			0.5	mA
SVR	Supply voltage rejection	$V_I = 8 \text{ to } 18 \text{ V}$ , $f = 120 \text{ Hz}$ , $I_O = 500 \text{ mA}$		68		dB
$V_d$	Dropout voltage	$I_O = 1 \text{ A}$ , $T_J = 25 \text{ }^\circ\text{C}$		2		V
eN	Output noise voltage	$T_A = 25 \text{ }^\circ\text{C}$ , $B = 10 \text{ Hz to } 100 \text{ kHz}$		10		$\mu\text{V}/V_O$
$R_O$	Output resistance	$f = 1 \text{ kHz}$		17		$\text{m}\Omega$
$I_{sc}$	Short circuit current	$V_I = 35 \text{ V}$ , $T_A = 25 \text{ }^\circ\text{C}$		0.2		A
$I_{scp}$	Short circuit peak current	$T_J = 25 \text{ }^\circ\text{C}$		2.2		A
$\Delta V_O/\Delta T$	Output voltage drift			-1.1		$\text{mV}/^\circ\text{C}$

- Load and line regulation are specified at constant junction temperature. Changes in  $V_O$  due to heating effects must be taken into account separately. Pulse testing with low duty cycle is used.

Note: Minimum load current for regulation is 5 mA.